



Product Datasheet

ESS Module

- Rated voltage 144VDC
- 63F capacitance
- Ultra-low ESR
- Stackable 19" rack design
- Laser welded connections
- Innovative cell management
- Integrated voltage and temperature monitoring
- CAN bus communication



ELECTRICAL SPECIFICATIONS	
Туре	M35W-144-0063
Rated Voltage V _R	144.00 V
Surge Voltage V _S ¹	148.80 V
Rated Capacitance C ²	63F
Capacitance Tolerance ³	0% / +20%
DC ESR ²	12 mΩ
Leakage Current I _L ⁴	<25 mA
Constant Current (ΔT = 15°C) 5 passive cooling	79 A
Constant Current (ΔT = 15°C) ⁵ active air cooling 60 CFM	177 A
Max Current I _{Max} ⁶	2.6 kA
Short Current I _S ⁷	12 kA
Stored Energy E 8	180 Wh
Energy Density E _d ⁹	5.6 Wh/kg
Usable Power DensityP _d ¹⁰	6.8 kW/kg
Impedance Match Power Density P _{dMax} 11	13.5 kW/kg

THERMAL CHARACTERISTICS	
Туре	M35W-144-0063
Working Temperature	-40 ~ 65°C
Storage Temperature ¹²	-40 ~ 70°C
Thermal Resistance R _{Th} ¹³ Passive cooling	0.2°C/W
Thermal Resistance R _{Th} ¹³ Active air cooling 60 CFM	0.04°C/W
Thermal Capacitance C _{Th} ¹⁴	36 kJ/°C

LIFETIME CHARACTERISTICS		
Туре	M35W-144-0063	
DC Life at High Temperature ¹⁵	1500 hours	
DC Life at RT ¹⁶	10 years	
Cycle Life ¹⁷	1'000'000 cycles	
Shelf Life ¹⁸	4 years	

		-		
SAFETY & ENVIRON	IMENTAL SPECIFICATIONS			
Туре		M35W-144-0063		
Safety		RoHS, REACH		
Vibration		Seismic Standard IEC 60068-3-3 Zone 3		
Rated insulation vo	tage (maximum series voltage)	1kVDC according Railway S	tandard IEC 62497-1	
SECH SA	Z.I. du Vivier 22, CH-1690 Villaz-St-Pierre	Phone: +41 26 552 52 00	info@sechsa.com	Page 1 of 2
Copyright © 2020	Switzerland	All Rights Reserved	www.sechsa.com	21-03-29






MONITORING AND CELL VOLTAGE MANAGEMENT (CMS)		
Туре	M35W-144-0063	
Connector	Phoenix MCV1.5/8-GF-3.81	
Auxiliary power supply	24V ± 10% 5W	
Cell Voltage Monitoring and Management ¹⁹	Microprocessor based, individual cell balancing	
Temperature Sensor	4x NTC (10kOhm @25°C)	
Communication interface	CAN bus 2.0A	

PHYSICAL PARAMETERS	
Туре	M35W-144-0063
Mass M, typical	32 kg
Power Terminals	M8 ²⁰
Dimensions ²¹ Length	555 mm
Width	483 mm
Height	150 mm

NOTES:

- Surge voltage V_S: Absolute maximum voltage, non-repetitive. The duration must not exceed 1 second.
- 2. Capacitance C: The test current is 0.075 A/F, if the calculated current is >100A, then apply 100A.



- 3. Capacitance tolerance: Typical tolerance is +5%~+10%.
- 4. Leakage current measurement procedure: 1) Charge the capacitor to the V_R with a constant current (0.075 A/F, if the calculated current is >100A, then apply 100A). 2) Hold the voltage at V_R for 72h. 3) The current to maintain V_R after 72 h is the leakage current.
- 5. Max constant working current: $I_{MCC} = \sqrt{\Delta T/(ESR * R_{Th})}$
- 6. Max current: $I_{Max}=0.5C*V_R/(\Delta t+ESR*C)$, discharge from V_R to V_R/2 in 1 second.
- 7. Short current: $I_5 = V_R / ESR$
- 8. Stored energy: $E = 0.5C * V^2/3600$
- 9. Energy density: $E_d = E/M$
- 10. Usable power density: $P_d = 0.125V_R^2/(ESR * M)$
- 11. Impedance match power density: $P_{dMax} = 0.25V_R^2/(ESR * m)$
- 12. Storage temperature: Storage in discharge state.
- 13. Thermal resistance: $R_{Th} = \Delta T/P$, where P=ESR * I²
- 14. Thermal capacitance is indicated for the whole module.
- 15. DC life at high temperature: Hold the capacitor charged at rated voltage at 65°C for 1500h. The capacitance shall be >80% of the rated value, the ESR shall be <200% of the rated value.</p>

- 16. DC life at RT: Hold the capacitor charged at rated voltage at room temperature RT, the capacitance shall be >80% of the rated value, the ESR shall be <200% of the rated value.
- 17. Cycle life: Charge and discharged the capacitor in the range between $V_{\rm R}$ and $V_{\rm R}$ /2. 5 seconds waiting period between charge and discharge. The constant test current is 0.075 A/F (if the calculated current >100A, then apply 100A).
- 18. Shelf life: Discharged and no load applied at RT.
- 19. See detailed CMS datasheet and user manual.
- 20. The maximum torque is 25Nm for M8.
- 21. 19" rack module with a height of 4U



Notes:

Standard markings:

- + Name of manufacturer, part number, serial number
- + Rated voltage and capacitance, negative and positive terminals, warning marking
- + Stored energy in watt-hours

The contents of this document are subject to change without notice. SECH accepts no liability for the accuracy or credibility of the values and information contained in this document.